

CHANNEL			VALUE	FUNCTION
47ch	15ch	11ch		
1	1	1	000-255	TILT 0°→220°
2	2	2	000-255	TILT FINE
3	3	3	000-255	TILT SPEED Fast to Slow
	4	4	000-255	RED 0%→100%
	5	5	000-255	GREEN 0%→100%
	6	6	000-255	BLUE 0%→100%
	7	7	000-255	WHITE 0%→100%
4			000-255	RED 1 0%→100%
5			000-255	GREEN 1 0%→100%
6			000-255	BLUE 1 0%→100%
7			000-255	WHITE 1 0%→100%
8			000-255	RED 2 0%→100%
9			000-255	GREEN 2 0%→100%
10			000-255	BLUE 2 0%→100%
11			000-255	WHITE 2 0%→100%
12			000-255	RED 3 0%→100%
13			000-255	GREEN 3 0%→100%
14			000-255	BLUE 3 0%→100%
15			000-255	WHITE 3 0%→100%

16			000-255	RED 4 0%→100%
17			000-255	GREEN 4 0%→100%
18			000-255	BLUE 4 0%→100%
19			000-255	WHITE 4 0%→100%
20			000-255	RED 5 0%→100%
21			000-255	GREEN 5 0%→100%
22			000-255	BLUE 5 0%→100%
23			000-255	WHITE 5 0%→100%
24			000-255	RED 6 0%→100%
25			000-255	GREEN 6 0%→100%
26			000-255	BLUE 6 0%→100%
27			000-255	WHITE 6 0%→100%
28			000-255	RED 7 0%→100%
29			000-255	GREEN 7 0%→100%
30			000-255	BLUE 7 0%→100%
31			000-255	WHITE 7 0%→100%
32			000-255	RED 8 0%→100%
33			000-255	GREEN 8 0%→100%
34			000-255	BLUE 8 0%→100%
35			000-255	WHITE 8 0%→100%
36				RED 9

			000-255	0%→100%
37			000-255	GREEN 9 0%→100%
38			000-255	BLUE 9 0%→100%
39			000-255	WHITE 9 0%→100%
40			000-255	RED 10 0%→100%
41			000-255	GREEN 10 0%→100%
42			000-255	BLUE 10 0%→100%
43			000-255	WHITE 10 0%→100%
44	8	8	000-007 008-015 016-131 132-139 140-181 182-189 190-231 232-239 240-247 248-255	STROBE Close Open Strobe from Slow to Fast Open Slow Open Fast Close from Slow to Fast Open Fast Open Slow Close from Slow to Fast Open Random Strobe from Slow to Fast Open
45	9	9	000-255	DIMMER 0%→100%
46	10	10	000-255	DIMMER FINE
	11		000-255	PIXEL EFFECT DIMMER 0%→100%
	12		000-009 010-014 015-019 020-024 025-029 030-034 035-039 040-044 045-049 050-054	PIXEL EFFECT COLOR Open LEE 790-Moroccan Pink LEE 157-Pink LEE 332-Special Rose Pink LEE 328-Follies Pink LEE 345-Fuchsia Pink LEE 194-Surprise Pink LEE 181-Congo Blue LEE 071-Tokyo Blue LEE 120-Deep Blue

			<p>055-059 060-064 065-069 070-074 075-079 080-084 085-089 090-094 095-099 100-104 105-109 110-114 115-119 120-124 125-129 130-134 135-139 140-144 145-149 150-154 155-159 160-164 165-169 170-174 175-179 180-201 202-207 208-229 230-234 235-239 240-244 245-249 250-255</p>	<p>LEE 079-Just Blue LEE 132-Medium Blue LEE 200-Double CT Blue LEE 161-State Blue LEE 201-Full CT Blue LEE 202-Half CT Blue LEE 117-Steel Blue LEE 353-Lighter Blue LEE 118-Light Blue LEE 116-Medium Blue Green LEE 124-Dark Green LEE 139-Primary Green LEE 089-Moss Green LEE 122-Fern Green LEE 738-JAS Green LEE 088-Lime Green LEE 100-Spring Yellow LEE 104-Deep Amber LEE 179-Chrome Orange LEE 105-Orange LEE 021-Gold Amber LEE 778-Millennium Gold LEE 135-Deep Gold Amber LEE 164-Flame Red Open Clockwise Rotation, Fast to Slow Stop Counter-clockwise Rotation, Slow to Fast Open Random Color: Fast Random Color: Medium Random Color: Slow Open</p>
	13		<p>000-003 004-007 008-011 012-015 016-019 020-023 024-027 028-031 032-035 036-039</p>	<p>PIXEL EFFECT SELECT Null Built-in Effect 1 Built-in Effect 2 Built-in Effect 3 Built-in Effect 4 Built-in Effect 5 Built-in Effect 6 Built-in Effect 7 Built-in Effect 8 Built-in Effect 9</p>

			040-043 044-047 048-051 052-055 056-059 060-063 064-067 068-071 072-075 076-079 080-083 084-087 088-091 092-095 096-099 100-103 104-107 108-111 112-115 116-119 120-123 124-127 128-131 132-135 136-255	Built-in Effect 10 Built-in Effect 11 Built-in Effect 12 Built-in Effect 13 Built-in Effect 14 Built-in Effect 15 Built-in Effect 16 Built-in Effect 17 Built-in Effect 18 Built-in Effect 19 Built-in Effect 20 Built-in Effect 21 Built-in Effect 22 Built-in Effect 23 Built-in Effect 24 Built-in Effect 25 Built-in Effect 26 Built-in Effect 27 Built-in Effect 28 Built-in Effect 29 Built-in Effect 30 Built-in Effect 31 Built-in Effect 32 Built-in Effect 33 Null
	14		000 001-127 128-255	PIXEL EFFECT SPEED Null Slow to Fast without Fade Slow to Fast with Fade
47	15	11	000-029 030-039 040-049 050-059 060-069 070-099 100-109 110-119 120-122 123 124 125	FUNCTION (To activate following functions, stop in DMX value for at least 3 seconds.) Null Dimmer Curve: Linear Dimmer Curve: Square Law Dimmer Curve: Inv SQ Law Dimmer Curve: S Curve Null Led Frequency Setting Enable Led Frequency Setting Disable Null 900Hz 1000Hz 1100Hz

			126	1200Hz
			127	1300Hz
			128	1400Hz
			129	1500Hz
			130	2500Hz
			131	4000Hz
			132	5000Hz
			133	6000Hz
			134	10000Hz
			135	15000Hz
			136	20000Hz
			137	25000Hz
			138-139	Null
			140-159	Null
			160-169	Invert Pixel Order: Yes
			170-179	Invert Pixel Order: No
			180-199	Null
			200-209	All Reset
			210-219	Dimmer Speed: Fast
			220-229	Dimmer Speed: Smooth
			230-255	Null